

SYSTEM ADMINISTRATOR PROGRAMMING



While your handset is on-hook, press

TRSF and then dial 200	DISPLAY SHOWS
Dial the four-digit password, 1234	[ENABLE CUS. PROG. PASSCODE]
Dial 1 to enable	[ENABLE CUS. PROG. - DISABLE]
Press TRSF . The keyset returns to its idle condition	[ENABLE CUS. PROG - ENABLE]

NOTE: You must begin programming within 30 seconds. Once you are in programming, any delay of more than 30 seconds between keystrokes will cause the system to automatically close programming.

PROGRAM SYSTEM SPEED DIAL NUMBERS

Open customer programming (as above) and follow the instructions below.

- | | |
|--|---|
| | DISPLAY SHOWS |
| 1. Press TRSF 705 | SYS SPEED DIAL |
| Display shows | 500: |
| 2. Dial 500 or speed bin desired (eg 505) | SYS SPEED DIAL |
| OR press UP or DOWN VOLUME to make the selection and press the right hand key to move the cursor (the MUTE key) | 505: |
| 3. Enter 9 (the system automatically inserts a dash) followed by the phone number and press the right hand key to save the phone number. Then return to step 2 and repeat the process. | SYS SPEED DIAL
505:9-121223456789 |
| |  Scroll
 |
| 4. Press TRSF to store and exit programming | |

PROGRAM SYSTEM SPEED DIAL NAMES

This procedure allows a name to be assigned for each system speed dial location, up to 11 characters. This name enables you to locate the speed dial number when you are using the directory dial feature.

ACTION	DISPLAY
1. Press TRSF 706	SYS SPEED NAME
Display shows	500:
2. Dial the system speed number (e.g., 505)	SYS SPEED NAME
OR press UP or DOWN to select the	505:
entry number and press the right hand key (MUTE) to move the cursor	
3. Enter the name	SYS SPEED NAME
	505: SAMSUNG
4. Press the right hand key to return to step 2 above	

HOLD deletes the entry

VOLUME keys push the cursor forwards and backwards if the next letter is on the same keypad as the previous ie **HOME**