

SAMSUNG DCS SYSTEM ADMINISTRATOR PROGRAMMING

CHANGING TIME & DATE

ENABLE PROGRAMMING

- While the handset is on-hook, press TRSF and dial 200

The display shows

```
ENABLE CUS PROG  
PASSCODE:
```

- Dial 1234

The display shows

```
ENABLE CUS PROG  
DISABLE
```

- Dial 1 to enable

The display shows

```
ENABLE CUS PROG  
ENABLE
```

- Press TRSF

You now have access to system programming. Please note that once enabled you have approximately 4 ½ minutes from your last key press in programming before the system disables System Administrator Programming as a safety measure.

CHANGE TIME & DATE

- Press TRSF and dial 505

The display shows

```
OLD: 1102703:1003  
NEW:WMMDDYY:HHMM
```

- Enter new time and date using the following guidelines:

W = Day of the week. 1 =Monday, 2 = Tuesday, 3 = Wednesday, etc.

MM = Month. 01 = January, 02 = February, 03 = March, etc.

DD = Date.

YY = Year.

HH = Hours. Use 24 hour clock.

MM = Minutes.

- Press TRSF to exit programming.